

## UNF Threads

Size	Major Dia	Threads Per Inch	Pitch	<u>P/4</u>	<u>P/8</u>	Pitch Dia	Minor Dia External	Minor Dia Internal	Minor Dia Area	Tensile Stress Area
inch	inch	tpi	inch	inch	inch	inch	inch	inch	sq. inch	sq. inch
#0	0.06	80	0.01250	0.00313	0.00156	0.0519	0.0451	0.0465	0.00151	0.0018
#1	0.073	72	0.01389	0.00347	0.00174	0.064	0.0565	0.058	0.00237	0.00278
#2	0.086	64	0.01563	0.00391	0.00195	0.0759	0.0674	0.0691	0.00339	0.00394
#3	0.099	56	0.01786	0.00446	0.00223	0.0874	0.0778	0.0797	0.00451	0.00523
#4	0.112	48	0.02083	0.00521	0.00260	0.0985	0.0871	0.0894	0.00566	0.00661
#5	0.125	44	0.02273	0.00568	0.00284	0.1102	0.0979	0.1004	0.00716	0.0083
#6	0.138	40	0.02500	0.00625	0.00313	0.1218	0.1082	0.1109	0.00874	0.01015
#8	0.164	36	0.02778	0.00694	0.00347	0.146	0.1309	0.1339	0.01285	0.01474
#10	0.19	32	0.03125	0.00781	0.00391	0.1697	0.1528	0.1562	0.0175	0.02
#12	0.216	28	0.03571	0.00893	0.00446	0.1928	0.1734	0.1773	0.0226	0.0258
1/4	0.25	28	0.03571	0.00893	0.00446	0.2268	0.2074	0.2113	0.0326	0.0364
5/16	0.3125	24	0.04167	0.01042	0.00521	0.2854	0.2629	0.2674	0.0524	0.058
3/8	0.375	24	0.04167	0.01042	0.00521	0.3479	0.3254	0.3299	0.0809	0.0878
7/16	0.4375	20	0.05000	0.01250	0.00625	0.405	0.378	0.3834	0.109	0.1187
1/2	0.5	20	0.05000	0.01250	0.00625	0.4675	0.4405	0.4459	0.1486	0.1599
9/16	0.5625	18	0.05556	0.01389	0.00694	0.5264	0.4964	0.5024	0.189	0.203
5/8	0.625	18	0.05556	0.01389	0.00694	0.5889	0.5589	0.5649	0.24	0.256
3/4	0.75	16	0.06250	0.01563	0.00781	0.7094	0.6763	0.6823	0.351	0.373
7/8	0.875	14	0.07143	0.01786	0.00893	0.8286	0.79	0.7977	0.48	0.509
1	1	12	0.08333	0.02083	0.01042	0.9459	0.9001	0.9098	0.625	0.663
1-1/8	1.125	12	0.08333	0.02083	0.01042	1.0709	1.0258	1.0348	0.812	0.856
1-1/4	1.25	12	0.08333	0.02083	0.01042	1.1959	1.1508	1.1598	1.024	1.073
1-3/8	1.375	12	0.08333	0.02083	0.01042	1.3209	1.2758	1.2848	1.26	1.315
1-1/2	1.5	12	0.08333	0.02083	0.01042	1.4459	1.4008	1.4098	1.521	1.581

Any use of the above information is done with the full understanding that Allied Titanium, Inc. or its representatives provide no engineering services or guarantees that the specifications above are accurate. Users of the above specifications should be advised to consult with an engineer to insure their accuracy and suitability for any application.